
### **Elastomer Solderless Compression Test Socket**

For BGA / Bumped chip / WLCSP / eMMC Package e **0.50 mm pitch** (from 0.50mm to 0.79mm)





### E-tec Interconnect AG is the world leading Test socket manufacturer

The Elastomer Solderless compression Test Sockets are ideal technical solution for good signal integrity with low signal loss. The sockets are available for any chip size and pitch and are attached with 2, 4 or 8 screws to the PCB. The socket outline will be kept to a minimum and special clearances can be offered to avoid components on the PCB.

SMT and thru-hole adapter sockets are available in certain pitches (contact factory for availability first) with these elastomer interposers to allow using this high frequency interposer on PCB's which have already been laid out for SMT or thru-hole sockets. We aim to solve your requirements. Please note, we will always request the chip data to ensure we offer a compatible socket.

		Contacts Specifications			
		Contact type code	E1	E2	E3
cifications contact ty		Application	High Frequency		
ng o or Concave tip	Curren Capaci Inducta	Mounting	Solderless	Solderless	Solderless
		Bandwidth (GAA2@-1dB)	17 GHz	34 GHz	>40 GHz
		Contact resistance	30 mOhm		
		-33 0 13 130 0	Gold Wire		
		PCB tip shape	Gold Wire		
		Force	20 gr to 50 gr		
		Current rating	2.5 A		
		Capacitance pF	0.14 pF	0.10 pF	0.06 pF
		Inductance nH	0.23 nH	0.30 nH	0.03 nH
		Impedance Ohms	41.3 Ω	47.1 Ω	51.1 Ω
		Temperature range	-40°C to +125°C		
		Mating cycles	1 K		

More on the next page



34

### **Elastomer Solderless Compression Test Socket**

For BGA / Bumped chip / WLCSP / eMMC Package e **0.50 mm pitch** (from 0.50mm to 0.79mm)




## Standard assembly boards

### **Small Chip size**

### **Medium Chip size**

Large Chip size







# **Custom assembly boards**







cifications

How to order

# BE# #### -05E# - # # # # # 55L #

### Shape of tip

E: Elastomer

# Nbr of contacts

Depends on ballcount of chip

## Contact type

- E1: High Frequency 17 GHz
- E2: High Frequency 34 GHz
- E3: High Frequency 40 GHz

# <u>Plating</u>

**55L:** Gold + Locating pegs

Grid code / Config. code

Will be given by the

factory after receipt of the chip datasheet

### Option code (see page 16-19)

- M: Multi frames
- U: Multi packages
- S: Custom opening slot
- H: Heatsink
- F: Fan + Heatsink
- W: Transparent lid
- I : Steel retention lid
- B: Aluminium retention lid
- G: Handling button

#### Retention frame type (Lid) (see page 12-15)

- W: TwistLock
- F:FastLock
- B:SpringLock
- H: Open Clamshell Alu (<200 contacts)
- J : Clamshell Alu (>200 contacts)
- L: Open Lever Clamshell Alu (>200 contacts)
- S: ScrewLock
- Q: Open QuickLock (<200 contacts)
- D: QuickLock (>200 contacts)
- M: Injection Molded ClamShell
- R: ReverseLock
- T: SlimLock

